

Most AC-powered electronic devices sold in the United States and Canada have an AC plug with two flat blades and operate with 110 or 120 volts AC power. Other countries use different AC outlet arrangements and AC power voltages. The Travel Voltage Converter lets you adapt to local power systems (220–240 volts) and use your electronic devices worldwide.

You can use the converter continuously, depending on the power rating of the appliance in use. Refer to this time usage chart based on your device's power rating.

Power Rating in Watts	Continuous Use in Minutes
1000	60
1500	30
2000	10

Cautions:

- Use this converter only with **non-electronic heating devices that have a power rating from 51~2000 watts**, such as hair dryers, irons, heating pads, coffee makers, steamers, manicure sets, heaters, hot shavers, toasters, lamps, and food/bottle warmers.
- DO NOT use with battery chargers, contact lense disinfectors, auto start/shut off irons, programmable coffee makers, hair straighteners or any electronically controlled heating appliances.
- Please consult your appliance's manufacturer or owners manual to ensure compatibility before using.

OPERATION

1. Use the charts on Page 2 to determine the AC voltage and outlet configuration of the country you are in. Then set up the converter as required.

- For Europe and the Middle East:

Push out the adapter plug marked **EUROPE** of this converter completely until it clicks into place. Then the Europe plug locks automatically.

After use: Just push this Europe adapter plug back into the converter directly.

- For the Philippines and Thailand:

Push out the adapter plug marked **S.A/SWIVEL** of this converter completely until it clicks into place. Turn the two blades parallel to match AC outlet's holes. Then the USA plug locks automatically.

After use: Just push this S.A/SWIVEL adapter plug back into the converter directly.

- For Australia and New Zealand:

Push out the adapter plug marked **AUST./N.Z.** of this converter completely until it clicks into place. Turn the two blades to the angle that matches the AC outlet's holes. Then this AUST./N.Z. plug locks automatically.

After use: Just push this AUST./N.Z. adapter plug back into the converter directly.

- For England, Africa, Singapore, and Hong Kong:

Push out the adapter plug marked **U.K.** of this converter completely until it clicks into place. Slide the plastic ground pin on top forward. Then this U.K. plug locks automatically.






After use: Push the ground pin back, then also push the U.K. adapter plug back.

2. Plug the converter into the AC wall outlet. The orange lamp lights.
3. Plug the electronic device into the AC outlet on the converter and turn on the device.

Notes:

- Be sure to disconnect the converter from the AC outlet when you are not using it.
- Some devices operate slightly slower when used in countries that provide 50Hz AC power. (The US and Canada operate at 60Hz AC.)
- Many countries have unstable voltage conditions that might prematurely shut off your device. This does not mean that your device or the converter is malfunctioning. If this happens, disconnect the converter from the AC outlet and let it cool down for about 30 minutes at room temperature.
- The converter contains a thermal circuit which shuts off automatically when it is overloaded. If this happens, disconnect the converter from the AC outlet and let it cool down for about 30 minutes at room temperature.

Outlet Configurations

Type A	Type B	Type C	Type D	Type E
				

Note: For countries that require adapter type E, you will need to purchase it separately from your local retailer.

Country	Adapter Type	Volts	Freq/Hz
Afghanistan	E	220	50
Albania	B	220	50
Algeria†	B, E	127/220	50
American Samoa†	A, B, C	120/220	50
Angola	B	220	50
Anguilla	D	240	50
Antigua/Barbuda	A, D	230	60
Argentina	B, C	220	50
Armenia	B	220	50
Australia	C	240	50
Austria	B	230	50
Azerbaijan	B	220	50
Azores	B, E	220	50
Bahrain	D, E	220	50
Bali	B	220	50
Bangladesh	B, E	220	50
Belarus	B	220	50
Belgium	B	230	50
Benin	E	220	50
Bhutan	B, D	220	50
Bolivia†	A, B	110/220	50
Bosnia-Herzegovina	B	220	50
Botswana	D, E	220	50
Brazil†	A, B	110/220	60
Bulgaria	B	220	50
Burkina	B	220	50
Burma (Myanmar)	D, E	230	50
Burundi	B	220	50
Cambodia†	A, B	120/220	50
Cameroon	B	220	50
Canary Islands	B	220	50
Cape Verde Islands	B	220	50
Central African Rep.	B	220	50
Chad	B, E	220	50

Country	Adapter Type	Volts	Freq/Hz
Chile	B	220	50
China	B, C	220	50
Comoros	B	220	50
Congo	B	220	50
Croatia	B	220	50
Curacao†	A, B	110/220	60
Cyprus	B, D	240	50
Czech Republic	B	220	50
Denmark	B	230	50
Djibouti	B	220	60
Dominica	B, D	230	50
Egypt	B	220	50
England	D, E	240	50
Eritrea	B, E	220	50
Estonia	B	220	50
Ethiopia	B, E	220	50
Fiji	C	240	50
Finland	B	230	50
France	B	230	50
Gabon	B	220	50
Gambia	D	220	50
Georgia	B	220	50
Germany	B	230	50
Ghana	B, D, E	220	50
Greece	B	230	50
Greenland	B	220	50
Grenada	B, D, E	230	50
Grenadines	B, D, E	230	50
Guadeloupe	B	220	50
Guinea	B	220	50
Hong Kong	D, E	220	50
Hungary	B	220	50
Iceland	B	220	50
India	B, E	220	50

Country	Adapter Type	Volts	Freq/Hz
Indonesia	B	220	50
Iran	B	220	50
Iraq	B, D, E	220	50
Ireland	D, E	220	50
Israel	B	230	50
Italy	B	230	50
Ivory Coast	B	220	50
Jordan	B, D	220	50
Kazakhstan	B	220	50
Kenya	B, D, E	240	50
Kirghizia	B	220	50
Korea†	A, B	110/220	50/60
Kuwait	B, D, E	240	50
Laos	A, B	220	50
Latvia	B	220	50
Lebanon	B	220	50
Lesotho	B, E	240	50
Libya	B, E	230	50
Liechtenstein	B	220	50
Lithuania	B	220	50
Luxembourg	B	230	50
Macao	B, E	220	50
Macedonia	B	220	50
Madagascar	B	220	50
Malawi	D	230	50
Malaysia	D	240	50
Mali	B	220	50
Malta	D	240	50
Martinique	B	220	50
Mauritania	B	220	50
Mauritius	B, D, E	230	50
Moldova	B	220	50
Monaco	B	220	50
Mongolia	B	220	50
Morocco	B, E	220	50
Mozambique	B	220	50
Myanmar (Burma)	D, E	230	50
Namibia	E	220	50
Nepal	B, E	220	50
Netherlands	B	230	50
New Zealand	C	230	50

Country	Adapter Type	Volts	Freq/Hz
Niger	B	220	50
Nigeria	D, E	230	50
Norway	B	230	50
Oman	D, E	240	50
Pakistan	B, E	230	50
Papua New Guinea	C	240	50
Paraguay	B	220	50
Peru†	A, B	110/220	50/60
Philippines†	A, B	110/220	60
Poland	B	220	50
Portugal	B, E	230	50
Qatar	D, E	240	50
Romania	B	220	50
Russian Federation	B	220	50
Rwanda	B	220	50
St. Kitts-Nevis	D, E	230	60
St. Lucia	D	240	50
St. Vincent	D	230	50
Saudi Arabia†	A, B, D	127/220	50/60
Scotland	D, E	220	50
Senegal	B	220	50
Seychelles	D, E	240	50
Sierra Leone	D, E	230	50
Singapore	B, D, E	230	50
Slovakia	B	220	50
Slovenia	B	220	50
Solomon Islands	C, D	220	50
Somalia	B	220	50
South Africa	E	230	50
Spain	B	230	50
Sri Lanka	E	230	50
Sudan	B, D	240	50
Surinam†	A, B	110/220	50/60
Swaziland	E	230	50
Sweden	B	230	50
Switzerland	B	230	50
Syria	B	220	50
Tahiti†	A, B	127/220	50/60
Tajikistan	B	220	50
Tanzania	D, E	230	50
Thailand	A, B	220	50

Country	Adapter Type	Volts	Freq/Hz
Tonga†	A, C	110/220	50/60
Trinidad & Tobago†	A, D	115/230	60
Tunisia	B	220	50
Turkey	B	220	50
Turkmenistan	B	220	50
Uganda	D, E	240	50
Ukraine	B	220	50
United Arab Emirates	D, E	220	50
Uruguay	B	220	50
Uzbekistan	B	220	50
Vietnam†	A, B	120/220	50
Wales	D, E	220	50
Western Samoa	C	230	50
Yemen	B, D, E	220	50
Yugoslavia (Former)	B	220	50
Zaire	B, E	220	50
Zambia	B, D	220	50
Zimbabwe	D, E	220	50

†Some countries have different voltage systems depending on the region. For these countries, check with local authorities for the area you are in to make sure the voltage system is not specified below 220 volts.

SPECIFICATIONS

Input.....220 to 240 V AC

Output..... 110 to 120 V AC 2000 watts

Specifications are typical; individual units may vary.
Specifications are subject to change and improvement without notice.

THE SOURCE - WARRANTY



The Source warrants that this product will be free from defects in materials and workmanship for a period of one (1) year from the date of purchase. Within this period, simply take the product and your proof of purchase to any The Source store or participating dealer and the product will be replaced (where available) without charge. Any product which has been subject to misuse or accidental damage is excluded from this warranty.

This warranty is only applicable to a product purchased through The Source company-owned stores or participating dealers in Canada where the warranty is included with the product. While this warranty does not confer any legal rights other than those set out above, you may have additional statutory rights which will vary under the laws of the various countries, states, provinces and other governmental entities in which The Source operates. This warranty is subject to all statutory rights you may have in Canada.

Imported by:
The Source,
Barrie, Ontario, Canada, L4M 4W5

Manufactured in China

For product support please visit
www.thesource.ca

© 2015 The Source
All rights reserved.



Please Recycle